



# Gooch & Housego



**AOM Driver**  
**Model: CHP150-3DC-D50**  
**P/N: 97-02910-15**  
**Rev: B**  
**2.5 Watt RF Driver for**  
**Acousto-Optic Modulators**

*Formerly: 1150AF-DINA-2.5HCR*

The CHP150-3DC-D50 provides up to 2.5 Watts of RF power for a frequency of 150 MHz.

Fully adjustable with the screw potentiometer from 0.5 to 2.5 Watts.

A standard TTL signal controls the output RF power from 0 to 100% of the adjusted maximum power.

This driver is well suited for 150 MHz AO modulators requiring moderate amounts of RF power (1.5 - 2.5 Watts). It also is a good fit for the 150 MHz fiber coupled Q-switches.

### Key Features:

- Output RF power 2.5 Watts
- RF ON/OFF ratio >50 dB
- Fast Analog modulation
- Constant RF output power design
- Conductive cooling through base plate

### Applications:

- AOM driver for pulse fiber laser
- AOM applications with fast modulation
- Acousto-optic Modulators

## General Specifications

### Modulation Input

Input Impedance	75 Ohms
Digital Input (SMC)	Standard TTL

### RF Output

Center Frequency (Fc)	150 MHz $\pm$ 0.1%
Output Power (SMA Female)	2.5 W
Rise/Fall Time	7 nsec Typ.
RF Contrast Ratio	50 dB min
Harmonic Distortion	-20 dBc Max
Output Impedance	50 Ohms
Output VSWR	1.5 : 1 Max
Power Supply Voltage	+24 V @ 775 mA Nominal

**Document**

**10/23/12**


**Control**

Contact: sales@goochandhousego.com      www.goochandhousego.com

As part of our policy of continuous product improvement we reserve the right to change the specification at any time.

Document: 97-02910-15-50 Rev: A

**AOM Driver**  
**Model: CHP150-3DC-D50**  
**P/N: 97-02910-15**



**Outline:**

Dimensions (inches)

